

## PowerMate 625



### Features

- Automatic voltage regulator (AVR)
- Protects sensitive electronics such as PC periphery and home entertainment equipment from the damaging effect of over-current and over-voltage conditions
- Varistor technology based surge protection
- Stabilized output voltage
- Wide input voltage range of 192V to 272V
- Extraordinary high and low voltage protection
- Equipped with easy to re-activate automatic fuse
- 625VA maximum output load
- Telephone or modem surge protection

### Technical Data

Product Type	Automatic voltage regulator
Capacity	625VA / 360W
Input	
➤ Voltage	230 VAC
➤ Voltage Range	192 – 272 VAC
➤ Frequency	50Hz/60Hz
AVR	
➤ Output	± 10 %
LED	
➤ Power on / off	Green LED
➤ AVR LED	Boost: green LED; buck: red LED
➤ Building fault LED	Green LED
➤ Regulation	Regulation: green LED; out of range: orange LED
Environment	
➤ Operating Temperature	0° - 40 ° C at full load
➤ Humidity	Relative, 0% ~ 90% (non condensing)
➤ Noise Level	< 40 db
Interface	
➤ Electrical Outputs	x2
➤ Telephone/Modem Jack	x2
Measurements	
➤ Dimensions (D x W x H)	200mm x 105mm x 140mm
➤ Weight	1.34 kg
Accessory	-

All rights reserved. Subject to error and change without notice.